

# Uniden Radios

**Model:** HR-2510

**Standard wiring:**

- 1-Audio
- 2-Shield
- 3-Transmit
- 4-Channel Up
- 5-Channel Down

**Astatic wiring:**

- 1-White
- 2-Shield and Blue
- 3-Red
- 4-N/C
- 5-N/C
- Yellow-N/C
- Black-N/C

**Sadelta:**

- 1-Shield
- 2-White
- 3-Brown
- 4-N/C
- 5-N/C
- Green-N/C

**Tuner:**

- 1-White
- 2-Shield and Red
- 3-Blue
- 4-N/C
- 5-N/C
- Yellow-N/C
- Black-N/C

---

**Model:** HR-2600

**standard wiring:**

- 1-Audio
- 2-Shield

- 3-Transmit
- 4-Channel Up
- 5-Channel Down

**Astatic wiring:**

- 1-White
- 2-Shield and Blue
- 3-Red
- 4-N/C
- 5-N/C
- Yellow-N/C
- Black-N/C

**Sadelta:**

- 1-Shield
- 2-White
- 3-Brown
- 4-N/C
- 5-N/C
- Green-N/C

**Tuner:**

- 1-White
- 2-Shield and Red
- 3-Blue
- 4-N/C
- 5-N/C
- Yellow-N/C
- Black-N/C

---

**Model: Lincoln  
standard wiring:**

- 1-Audio
- 2-Shield
- 3-Transmit
- 4-Channel Up
- 5-Channel Down

**Astatic wiring:**

- 1-White
- 2-Shield and Blue
- 3-Red

4-N/C  
5-N/C  
Yellow-N/C  
Black-N/C

**Sadelta:**

1-Shield  
2-White  
3-Brown  
4-N/C  
5-N/C  
Green-N/C

**Tuner:**

1-White  
2-Shield and Red  
3-Blue  
4-N/C  
5-N/C  
Yellow-N/C  
Black-N/C

---

**Model:** Washington  
**standard wiring:**

Pin1=Audio  
Pin2=Shield  
Pin3=Receive  
Pin4=Switching Wire  
Pin5=Transmit

**Astatic wiring:**

Pin1=White  
Pin2=Shield  
Pin3=Black  
Pin4=Blue  
Pin5=Red

**Sadelta:**

Pin1=White  
Pin2=N/C  
Pin3=Green  
Pin4=Shield

Pin5=Brown

**Turner:**

Pin1=White  
Pin2=Shield  
Pin3=Black  
Pin4=Red  
Pin5=Blue

---

**Model: Grant XL**

**standard wiring:**

Pin1=Audio  
Pin2=Shield  
Pin3=Receive  
Pin4=Switching Wire  
Pin5=Transmit

**Astatic wiring:**

Pin1=White  
Pin2=Shield  
Pin3=Black  
Pin4=Blue  
Pin5=Red

**Sadelta:**

Pin1=White  
Pin2=N/C  
Pin3=Green  
Pin4=Shield  
Pin5=Brown

**Turner:**

Pin1=White  
Pin2=Shield  
Pin3=Black  
Pin4=Red  
Pin5=Blue

---

[Back](#)