

Channel Number	Reception Frequencies Mhz	Divide Ratio (N)	1st Local Oscillator Frequencies Mhz			1st IF Frequencies (Mhz)
			AM Mode	USB Mode	LSB Mode	
1	26.965	79	34.765	34.7665	34.7635	7.8
2	.975	80	.775	.7765	.7735	"
3	.985	81	.785	.7865	.7835	"
4	27.005	83	.805	.8065	.8035	"
5	.015	84	.815	.8165	.8135	"
6	.025	85	.825	.8265	.8235	"
7	.035	86	.835	.8365	.8335	"
8	.055	88	.855	.8565	.8535	"
9	.065	89	.865	.8665	.8635	"
10	.075	90	.875	.8765	.8735	"
11	.085	91	.885	.8865	.8835	"
12	.105	93	.905	.9065	.9035	"
13	.115	94	.915	.9165	.9135	"
14	.125	95	.925	.9265	.9235	"
15	.135	96	.935	.9365	.9335	"
16	.155	98	.955	.9565	.9535	"
17	.165	99	.965	.9665	.9635	"
18	.175	100	.975	.9765	.9735	"
19	.185	101	.985	.9865	.9835	"
20	.205	103	35.005	35.0065	35.0035	"
21	.215	104	.015	.0165	.0135	"
22	.225	105	.025	.0265	.0235	"
23	.255	107	.055	.0565	.0535	"
24	.235	106	.035	.0365	.0335	"
25	.245	108	.045	.0465	.0435	"
26	.265	109	.065	.0665	.0635	"
27	.275	110	.075	.0765	.0735	"
28	.285	111	.085	.0865	.0835	"
29	.295	112	.095	.0965	.0935	"
30	.305	113	.105	.1065	.1035	"
31	.315	114	.115	.1165	.1135	"
32	.325	115	.125	.1265	.1235	"
33	.335	116	.135	.1365	.1335	"
34	.345	117	.145	.1465	.1435	"
35	.355	118	.155	.1565	.1535	"
36	.365	119	.165	.1665	.1635	"
37	.375	120	.175	.1765	.1735	"
38	.385	121	.185	.1865	.1835	"
39	.395	122	.195	.1965	.1935	"
40	.405	123	.205	.2065	.2035	"