

TOM'S MIC WIRING GUIDE



COBRA RADIOS

Models:21,25,29,89GTL,1000GTL

microphone	wiring code
Standard	1-Shield,2-Audio,3-Transmit, 4-Receive
Astatic	1-Shield&Blue,2-White,3-Red,4- Black
Turner	1-Shield&Red,2-White,3-Blue,4- Black
Sadelta	1-Shield,2-White,3-Brown,4- Green

COBRA RADIOS

Models:18RV,19X,19 PLUS,20 PLUS

microphone	wiring code
Standard	1-Audio,2-Transmit,3-N/C,4-Shield, 5-Receive
Astatic	1-White,2-Red,3-N/C,4-Shield&Blue, 5-Black- Yellow-N/C
Turner	1-White,2-Blue,3-N/C,4-Shield&Blue, 5-Black- Yellow-N/C
Sadelta	1-White,2-Brown,3-N/C,4-Shield, 5-Green

COBRA RADIOS

Models:90,140GTL,142GTL,148GTL, 2000GTL,2010

microphone	wiring code
Standard	1-Audio,2-Shield,3-Receive,4- Switching,5-Transmit
Astatic	1-White,2-Shield,3-Black,4-Blue, 5-Red- Yellow-N/C
Turner	1-White,2-Shield,3-Black,4-Red, 5-Blue- Yellow-N/C
Sadelta	1-White,2-N/C,3-Green,4-Shield, 5-Brown

COBRA RADIOS

**Models:18ULTRA/LTD,19/ULTRA/LTD/DX LTD/GTL,21XLR/GTL/LTD/Classic,25GTL/LTD/
ClassicGold/LTDWX,26Classic/PLUS,29XLR/ LTD/Classic/WX/ST/PLUS,31PLUS,33PLUS,
40X,77X,78X,86XLR,87GTL,CAM89,89XLR,93LTDWX,135XLR,138XLR,139XLR,146GTL,148GTLDX/GTLB**

microphone	wiring code
Standard	1-Shield,2-Audio,3-Transmit,4- Receive
Astatic	1-Shield & Blue,2-White,3-Red,4- Black
Turner	1-Shield & Red,2-White,3-Blue,4- Black
Sadelta	1-Shield,2-White,3-Brown,4- Green

UNIDEN RADIOS

Models:HR-2510,HR-2600,Lincoln

microphone	wiring code
Standard	1-Audio,2-Shield,3-Transmit,4- Channel Up,5-Channel Down
Astatic	1-White,2-Shield&Blue,3-Red,4-N/C, 5-N/C, Yellow&Black-N/C
Sadelta	1-Shield,2-White,3-Brown,4-N/C,5-N/C ,Green-NC
Turner	1-White,2-Shield&Red,3-Blue,4-N/C, 5-N/C, Yellow&Black-N/C

PRESIDENT RADIOS**Models: Washington, Grant XL, Madison**

microphone	wiring code
Standard	1-Audio,2-Shield,3-Receive,4- Switching, 5-Transmit
Astatic	1-White,2-Shield,3-Black,4-Blue, 5-Red
Sadelta	1-White,2-NC,3-Green,4-Shield, 5-Brown
Turner	1-White,2-Shield,3-Black,4-Red, 5-Blue


GALAXY RADIOS**Models: 2100, 33Plus, DX33HML, DX44V, DX55, DX66V, DX77HML, DX77V, DX88HML, Jupiter, Mars, Mirage, Mirage44, Pluto, Saturn, Saturn2, Sirius, Super Galaxy**

microphone	wiring code
Standard	1-Shield,2-Audio,3-Transmit, 4-Receive
Astatic	1-Shield&Blue,2-White,3-Red,4-Black Yellow-NC
Sadelta	1-Shield,2-White,3-Brown,4-Green
Turner	1-Shield&Red,2-White,3-Blue,4-Black Yellow-NC

REALISTIC RADIOS**Models:TRC-24A,TRC-24B,TRC-30, TRC-30A,TRC-55,TRC-56,TRC-57,TRC-67, TRC-410,TRC-412,TRC-413,TRC-414,TRC-415, TRC-417,TRC-420,TRC-421,TRC-421A, TRC-422A,TRC-424,TRC-425,TRC-426, TRC-427,TRC-428,TRC-430,TRC-431,TRC-432, TRC-433,TRC-434,TRC-440,TRC-441,TRC-448, TRC-449,TRC-450,TRC-451,TRC-452,TRC-453, TRC-454,TRC-455,TRC-456,TRC-457,TRC-458, TRC-459,TRC-460,TRC-461,TRC-462,TRC-466, TRC-467,TRC-468,TRC-469,TRC-470,TRC-473, TRC-477,TRC-479,TRC-480,TRC-482,TRC-490, TRC-492,TRC-500**

microphone	wiring code
Standard	4-Audio,1-Shield,2-N/C,5-Receive, 3-Transmit
Astatic	4-White,1-Shield&Blue,2-N/C,5-Black, 3-Red
Sadelta	4-White,1-Shield,2-N/C,5-Green, 3-Brown
Turner	4-White,1-Shield&Red,2-N/C,5-Black, 3-Blue

[BACK TO MAIN PAGE](#)

Smaller devices, higher performance
MSP430FG6x MCUs
 High analog integration plus USB and LCD
 **Sample now**

BUILD A FREE WEBSITE ON

Angelfire Sponsored by 